

Copper Alloy	Cu	Sn	Pb	Zn	Fe	Ni	P	Al	Mn	Si	Sb	S	Impurities
High Tensile Brass													
G-CuZn34Al2	55-66			Rem.	0.5-2.5	3		1-3	0.3-4				0.5
G-CuZn35Al1	56-65			Rem.	0.5-2	2		0.5-2	0.3-3				1.5
CuZn23Al6	63-65.5		1	Rem.	2-3.5	0.5		5-7	3.5-5				0.2
CuZn23Al6Mn4Fe3Pb(CW704R)	63-65	0.2	0.2-0.8	Rem.	2-3.5	0.5		5-6	3.5-5	0.2			0.2
CuZn25Al5Fe2Mn2Pb(CW705R)	65-68	0.2	0.2-0.8	Rem.	0.5-3	1		4-5	0.5-3				0.3
CuZn35Ni2	58-61	0.5	0.8	Rem.	0.5	2-3		0.3-1.5	1.5-2.5	0.1			0.5
CuZn35Ni3Mn2AlPb(CW710R)	58-60	0.5	0.2-0.8	Rem.	0.5	2-3		0.3-1.3	1.5-2.5	0.1			0.3
CuZn38Al	59-61.5	0.3	1	Rem.	1	0.6		0.3-1.3	0.6-1.6	0.5			0.5
CuZn38Mn1Al(CW716R)	59-61.5	0.3	1	Rem.	1	0.6		0.3-1.3	0.6-1.8	0.5			0.3
CuZn40Al1	57.5-60	0.4	0.8	Rem.	1	1		0.4-1.3	0.8-1.8	0.7			0.5
CuZn40Mn1Pb1(CW720R)	57-59	0.3	1-2	Rem.	0.3	0.6		0.2	0.5-1.5	0.1			0.3
CuZn40Mn1Pb1AlFeSn(CW721R)	57-59	0.2-1	0.8-1.6	Rem.	0.2-1.2	0.3		0.3-1.3	0.8-1.8				0.3
CuZn40Mn1Pb1FeSn(CW722R)	56.5-58.5	0.2-1	0.8-1.6	Rem.	0.2-1.2	0.3		0.1	0.8-1.8				0.3
CuZn40Mn2	57-59	0.5		Rem.	1.5	1		0.1	1-2.5	0.1			0.5
CuZn40Mn2Fe1(CW723R)	56.5-58.5	0.3	0.5	Rem.	0.5-1.5	0.6		0.1	1-2	0.1			0.4
G-CuZn40Fe	56-62	1		Rem.	0.2-1.2	2			2.5				1.2